




## **CXiR** True diversity in-camera receiver

	
<b>Frequency range</b>	470MHz - 1000MHz
<b>Switching bandwidth</b>	Up to 24MHz
<b>Number of switchable frequencies built in</b>	Up to 32
<b>Sensitivity</b>	98dBm for 40dB SINAD
<b>LED indicators for</b>	Low transmitter battery
<b>No carrier</b>	32 (selectable in 25kHz steps)
<b>Diversity active receiver</b>	Wideband FM
<b>CXiR supply range</b>	7-18 volts DC, 150-55mA
<b>System frequency response</b>	50Hz to 18KHz $\pm$ 1dB
<b>System THD</b>	<0.2% typical
<b>Signal to noise ratio</b>	96 to over 104dB
<b>Size</b>	98 (h) x 60 (w) x 18 (d) mm
<b>Weight</b>	150g
<b>Operating temperature range</b>	-20° to +55°C
<b>Compliant to</b>	ETS 300422 EN 300445 (CE)FCC

For further information contact Audio Ltd or your local distributor. [www.audioltd.com](http://www.audioltd.com)