



## **TXiR** Pocket transmitter



<b>Frequency range</b>	470MHz – 1000MHz
<b>Switching bandwidth</b>	Up to 24MHz
<b>Frequency stability</b>	Better than ETS 300-422
<b>Number of frequencies</b>	32 Pre-programmed
<b>Output power</b>	50mW nominal
<b>Gain control range</b>	28dB in 8 steps, plus 2 steps for 600Ω line input
<b>Maximum input level</b>	+6dB gain setting 0, 600Ω
<b>Frequency response</b>	50Hz to 18Khz ±1dB
<b>THD</b>	< 0.1% at working levels < 0.3% at gain position 7 with -6dB input in overload
<b>Battery required</b>	9V (IEC 6LR61) Alkaline
<b>Battery life</b>	Typically 5 hours
<b>Size</b>	89 (h) x 60 (w) x 21 (d) mm
<b>Weight</b>	135g
<b>Operating temperature range</b>	-20° to +55° C
<b>Compliant to</b>	ETS 300422 EN 300445 (CE) FCC

For further information contact Audio Ltd or your local distributor. [www.audioltd.com](http://www.audioltd.com)